

SK-50  
6M  
STACKING HARNESS

1. Mount the antennas 12'-15' apart. This distance is not critical and 6" or so either direction will result in no observable change in performance.
- 2 Both antennas should be mounted with connectors facing down and the square radiator sections parallel with one another. That is, when viewed from above, the top antenna would exactly block the view of the bottom antenna.
3. Tune each antenna separately, then attach the harness. Further tuning may not be necessary, but if it is, all 5/16" tubes should be moved in equal increments and in the same direction.
4. Excess coax may be coiled and secured with the included tie wraps.
5. UHF connectors are not watertight. Our preferred method to seal them is to wind an overlapping spiral of quality electrical tape, starting from the joint of the connector/socket out on to the RG6/U. The 'tail of the tape is then secured from unwinding with a black tie wrap.

**CAUTION: These cables are precision cut 75 ohm lines. Do NOT cut them. Coil the excess cable.**

**PAR ELECTRONICS**  
P.O. BOX 645  
GLENVILLE, NC 28736  
  
VOICE (828)743-1338  
FAX (828)743-1219  
E-Mail [par@parelectronics.com](mailto:par@parelectronics.com)



CQ VHF CONTEST WINNING STATION AT  
W4VHF  
FEATURING STACKED OA-50'S